

N I M

4 C H Linear Sum Amp (N004)



- ◎ Linear signal of 8 input is added and output from two NIM connectors.
- ◎ Input impedance 50 Ω
Output impedance 50 Ω
- ◎ Raiztaim <5nSec
- ◎ To the output 0 ~ -2V (40mA), the negative input type of the correspondence.

It is the most suitable for the addition of the counter signal.

< Specifications >

INPUT

Connector	:	LEMO connector
Impedance	:	50 Ω
Input range	:	0V ~ -2V

OUTPUT

Connector	:	LEMO connector
Polarity	:	The same polarity to the input
Output range	:	0V ~ -2V
Impedance	:	50 Ω
Delay	:	~5 nSec
Form	:	NIM standard 1 width module
Power supply	:	+6V 300mA
		+12V 200mA
		-6V 400mA
		-12V 400mA